



T.			U_f	I_f	Cl.	U_a	U_{g2}	U_{g1}	I_a	I_{g2}	I_{g1}	$U_{g1 \approx}$	P_{dr}	P_o	P_{g2}	P_a
			V	A		V	V	V	mA	mA	mA	V	W	W	W	W
RS 1003	Sim	1	6,3	2,3	C-Tgr $f < 30$ MHz C-Tgr $f = 100$ MHz C-Tlf A-Mod $f < 30$ MHz B-Tlf $f < 30$ MHz stat. stat. max.	600	300	— 30	208	33	16	46	0,74	83	10	42
						800	335	— 35	207	29	15	50	0,75	113	9,7	53
						1000	340	— 45	215	29	14	62	0,87	155	10	60
						300	300	— 25	163	30	14	40	0,55	26	9	23
						600	350	— 30	193	26	14	45	0,65	70	9	46
						800	380	— 35	200	25	14	50	0,7	105	9,5	55
						800	300	— 90	130	25	14	110	1,5	70	7,5	36
						1000	430	— 18	80	7		10		23		
						400	400	— 200	100							
						1000	600									

$S = 18 \text{ mA/V}; \mu_{(g2/g1)} = 20$
 $P_{g1} = 0,5 \text{ W}; I_k = 260 \text{ mA}; U_{fk} = 200 \text{ V}; f = 150 \text{ MHz}$

C_{g1}	C_a	$C_{g1/a}$
pF	pF	pF
23	13	0,15

Equivalent

SRS 551	RFT
---------	-----

