

HALF-WAVE VACUUM RECTIFIER

For television damper service GENERAL DATA Electrical: Heater, for Unipotential Cathode: Voltage (AC or DC). 6.3 ± 10% volts Current 1.2 amp Direct Interelectrode Capacitances (Approx.):0 Plate to cathode and heater . . μμf Cathode to plate and heater. 8 щuf Heater to cathode . . . μμf Mechanical: Operating Position. . Any Maximum Överall Length. . Maximum Seated Length . 2-3/4" Maximum Diameter. . . 1-9/32Dimensional Outline . See General Section Bulb. Intermediate-Shell Octal 5-Pin. Arrangement 2 (JEDEC Group 1, No. B5-82), Intermediate-Shell Octal 6-Pin, Arrangement 1 (JEDEC Group 1, No.B6-8), Short Intermediate-Shell Octal 5-Pin with External Barriers, Arrangement 2 (JEDEC Group 1, No.B5-85), or Short Intermediate-Shell Octal 6-Pin with External Barriers, Arrangement 1 (JEDEC Group 1, No. B6-60) Basing Designation for BOTTOM VIEW Pin 1 d - Same as Pin 3 - Cathode (3 Pin 2 Pin 5 - Plate Pin 2 - Internal Pin 7 - Heater Connection-Pin 8 - Heater Do Not Use DAMPER SERVICE Maximum Ratings, Design-Maximum Values: For operation in a 525-line, 30-frame system PEAK INVERSE PLATE VOLTAGE* . 4400 max. volts 900 max. ma DC PLATE CURRENT. . . 155 max. ma max. watts

volts

volts

Heater negative with respect to cathode . 4400 max.

Heater positive with respect to cathode . 300 max.





HALF-WAVE VACUUM RECTIFIER

HADF-WAVE VACCOM RECTIFIER	
Characteristics:	
Tube-Voltage Drop for plate	_ ,
ma. = 250	volts
Without external shield.	
on the 5-pin bases, pin 1 as well as pins 4 and 6 is omitted.	1
Socket terminals 1,2,4 and 6 should not be used as tie points.	
Television Broadcast Stations, Federal Communications Commi	ssion.
* This rating is applicable when the duty cycle of the voltage puls	e does
not exceed 15 per cent of one horizontal scanning cycle. In line, 30-frame system, 15 per cent of one horizontal scanning cy	cle is
10 microseconds. A The dc component must not exceed 900 volts.	
# The dc component must not exceed 100 volts.	
•	
}	