### DESCRIPTION AND RATING

# TEMPERATURE-CONTROLLED IGNITRON GL-6513

The GL-5513 ignitron is a sealed, stainless-steel-jacketed, water-cooled, mercury-pool tube designed for rectifier service in the 125-, 250-, 600-, and 900-volt d-c power fields. It is suitable for use in rectifiers rated up to 1000 kilowatts output, depending on the number of ignitrons used, the output voltage, and the circuit. Continuous average current rating is 200 amperes per tube in such service. The tube is also designed for 2400-volt a-c control service where it has a rating of 2400 kilovolt-amperes.

This tube is identical in ratings and characteristics to the GL-5555/FG-238-B. Mechanically, it has the additional feature of an integral temperature-control device with protective features. The control includes a switch which operates a solenoid valve in the water-supply line to the tube in response to increasing and decreasing tube temperature, thus maintaining the amount of cooling water to the minimum required by the operating conditions. It also includes an over-temperature switch which may be used to remove power from the ignitron when its temperature exceeds a safe value.

This new construction prevents excessive condensation over the external parts of the tube under conditions of high humidity. Another advantage is the appreciable saving in maintenance costs over tubes of the old design since this control feature, in addition to greatly reducing the amount of water required, eliminates the necessity for such safety devices as water-flow relays, water over-temperature relays, and water-pressure interlocks required with the older design tubes. In applications where the cooling water flows through or three tubes in series this tube can be used with the GL-5555/FG-238-B since the control the position nearer the water drain where it receives the warmer water, can control the flow to all under normal conditions.

Like its prototype, the GL-6513 has an auxiliary anode and two ignitors. Excitation of the auxiliary anode permits stablizing the cathode spot for very small anode currents. The two ignitors assure long life since only one is used at a time. Phase control of the ignitor impulses permits voltage control of the rectified output. In common with other ignitrons are losses in the GL-6513 are low, and design and construction features inherent in the steel-jacketed construction assure ease of installation, economical use of space, and reliability of operation.

# TECHNICAL INFORMATION

#### GENERAL

## Electrical

Cathode Excitation - Cyclic
Cathode Spot Starting ~ Ignitor
Number of Electrodes
Main Anodes
Main Cathodes
Auxiliary Anodes
Ignitors

1 1 1

2

GENERAL ELECTRIC COMPANY

Electrical (Co	nt	۱d)
----------------	----	-----

Electrical (vont t)			
Arc Drop at 600 Peak Amperes	16.2	<u>+</u> 0.5	Volts
Cathode Excitation Requirements		_	
Ignitor Voltage Required to Fire		450	Volts
Ignitor Current Required to Fire		45	Amperes
Starting Time at Required Voltage or Current		100	Microseconds
annially arms as modernous torondo as a mission		-00	
Mechanical			
Envelope Material - Stainless Steel			
Net Weight		25	Pounds
Thermal			
Type of Cooling - Water		-150	, fo
Inlet Water Temperature, minimum		D-, D-	C
Inlet Water Temperature*, maximum			•
Power-Rectifier Service			
Peak Inverse Anode Voltage = 900 Volts		50	C
_ ·			C
Peak Inverse Anode Voltage = 2100 Volts		35	C
AC Control Service			^
Voltage = 2400 Volts RMS		<b>2</b> 5	C
Water Flow, minimum		7	College man Minute
At Continuous Rated Average Current		3	Gallons per Minute
Characteristics for Water Cooling at Rated Minis	num Flow		
Water Temperature Rise, maximum		7	С
Pressure Drop at 3 Gallons per Minute, maximum	n	6	Pounds per Square
. , ,			Inch
MAXIMUM RATINGS AND TYPICAL OPERATION			
Power-Rectifier Service, Continuous Duty			
Ratings are for Zero-Phase-Control			
Maximum Peak Anode Voltage			
Inverse	900	2100	Volts
Forward	900	2100	Volts
Maximum Anode Current	700		10115
Peak	1800	1200	Ammeres
	1800	1200	Amperes
Average	300	150	Ammanaa
Continuous	200	150	Amperes
Two-Hours - Averaged Over Any Two-Minute Inter		225	Amperes
One-Minute - Averaged Over Any One-Minute Inter		300	Amperes
Fault	12,000	9000	Amperes
Maximum Duration of Fault Current	0.15	0.15	Seconds
Frequency Range	25–60	25-60	Cycles per Second

AC Control Service #		
Two Tubes in Inverse Parallel, Ratings per Tube		
Voltage	2400	
Maximum Demand	5400	<b>-</b>
Average Current at Maximum Demand	135	<del>-</del>
Maximum Average Current	207	Amperes
Demand at Maximum Average Current	1105	
Maximum Averaging Time at 2400 Volts RMS	1.66	
Maximum Peak Fault Current	6000 -3000 25-60	
Frequency Range	27-00	Cycles per Second
Ignitor		
Maximum Voltage		
Positive - Anode Voltage	-	<del>-</del>
Negative	5	Volts
Maximum Current	100	A
Peak Root Mean Square	100	
Average	15 2	
Maximum Averaging Time	10	
Auxiliary-Anode		
Maximum Peak Forward Voltage	160	Volts
Maximum Peak Inverse Voltage		
Main Anode Conducting	25	
Main Anode Not Conducting	160	Volts
Maximum Current		
Peak	30	_
Average	9	
Maximum Averaging Time	10	
Root Mean Square	15	Amperes
Temperature-Control-Switch Ratings $ ot \pm$		
Maximum Voltage	575	Volts
Maximum Current	,	
Over-Temperature Switch	6	<u> </u>
Water-Control Switch	1.5	Amperes
Maximum Peak Potential of Tube Water Cylinder	1500	Volts
Above Ground Switch-Contact Arrangement	1500	107.09
Over-Temperature Switch - Normally Closed		
(Contacts Open on Temperature Rise)		
Water-Control Switch - Normally Open		
(Contacts Close on Temperature Rise)		

- \* No more than three tubes should be connected in series for water flow. When the series connection is used the temperature of the incoming water must be within the rated limit for the warmest tubes in the series.
- # RMS demand voltage, current, and kilovolt-ampere demand are all on the basis of full-cycle conduction (no phase delay) regardless of whether or not phase control is used.
- J Suitable fuses should be provided in the switch circuits to prevent a power arc should a ground occur in the switch or wiring.

November 16, 1954

TUBE DEPARTMENT

GENERAL ELECTRIC COMPANY

SCHENECTADY 5, NEW YORK

